

# Auto Zero



- ❖ Hold button to turn OFF
- ❖ Continue to hold button down after monitor turns OFF
- ❖ Monitor will read “Continue holding to calibrate or zero” and count down to zero

# Auto Zero



❖ H<sub>2</sub>S, CO and LEL Auto Zero, while O<sub>2</sub> sets to 20.9 %

**\* It is crucial that you are in fresh air, FREE of Gas, when performing this function.**

# Auto Zero



❖ When “Apply Gas” displays, press the blue button to return to normal operation. If you do not push the blue button at this point the monitor will see it as a fail calibration.